


Power Inverter 1200W TE16

For mobile use of various electronic devices via 12V connection



- Power Inverter DC 12V to AC 230V
- 2x 5V Output USB Ports
- 2x 230V Sockets with Power Switch
- High & Low Voltage Protection
- 1200W continuously Output Power
- Overcurrent Protection
- Automatical Turn Off with Alarm
- Built-in Ventilation Fan

- 2x 5V USB ports with max. 3.1A (in total)
- 2x 230V safety contact sockets with power switch
- Converts 12V DC battery power into standard 230V AC (household) power, to run a variety of electronics, e.g. tablets, smartphones, laptop computers, game systems, TVs, DVD/MP3 players, camping accessories, GPS units and much more
- Output power max. 1200W (continuous) & 2400W (peak)
- Automatic safety shutdown to secure the car battery (alarm at ~10.5V & ~16V)
- Protection against overload, short circuit & reverse polarity
- Overheating protection through built-in ventilation

Technical Specifications:

- Input voltage of the battery DC 12V (10.5V–16V)
- Output voltage per socket AC 230V / AC frequency 50Hz nominal
- Circuit protection (DC overload): 3x 40A internal fuses
- Cable length 2x 90cm
- Weight / Dimensions: 2.3 kg / (L) 28.8 x (W) 15.9 x (H) 9.9cm

Package Contents:

- Power Inverter 1200W TE16
- 2x 90cm connection cables
- User Manual

Article-No. 4753

